

Addressable Fire Alarm Bell

General

The **RK-624** addressable fire alarm bell connect to addressable fire alarm control panel. Up to 300 devices can be connected to each loop of RCL-3100 fire alarm control panel. The RK-624 has a bell sound when the fire alarm control panel is triggered.



Features

- DCP protocol for fast and robust communication
- Use standard cable, no shielded or twisted pair required on SLC loop
- Up to 300 devices can be used on per loop
- Low current consumption
- Electronic address is easily to program by RCL-3100 panels or programmer tool

Specifications

Model	RK-624
Operating Voltage	DC 24V
Quiescent current	1.2mA / DC 24V
Alarm current	30mA / DC 24V
Operating temperature	0°C ~ 50°C,
Relative humidity	< 95% RH, non-condensing
Material / color	Fire-proof plastics / Black
Dimensions	150Φx 58(D) mm